



9mm LES

Standard Series Vibrant Series V80

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ●● | ● | ● | 80+ | 350 | 7.4 | 10 |
| 1300lm | | ● | ●● | ● | ● | 80+ | 700 | 15.6 | 18.5 |
| 2000lm | | ● | ●● | ● | ● | 80+ | 1050 | 30.2 | 33 |

Designer Series

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ● | ● | ● | 90+ | 700 | 7.8 | 10.5 |
| 1300lm | | ● | ● | ● | ● | 90+ | 700 | 15.6 | 18.5 |
| 2000lm | | ● | ● | ● | ● | 90+ | 1050 | 30.2 | 34.1 |

Artist Series Vibrant Series V98

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ●● | ● | ● | 98 | 500 | 10.9 | 13.5 |
| 1300lm | ● | ● | ●● | ● | ● | 98 | 1050 | 24.3 | 27 |
| 2000lm | | ● | ●● | ● | ● | 98 | 1400 | 42.1 | 45 |

19mm LES

Standard Series Vibrant Series V80

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ●● | ● | ● | 80+ | 350 | 4.5 | 6.5 |
| 1300lm | | ● | ●● | ● | ● | 80+ | 700 | 9.6 | 12.3 |
| 2000lm | | ● | ●● | ● | ● | 80+ | 700 | 15.2 | 19.2 |
| 3000lm | | ● | ●● | ● | ● | 80+ | 1050 | 25.6 | 29.4 |
| 4000lm | | ● | ●● | ● | ● | 80+ | 1400 | 34.2 | 39.1 |
| 5000lm | | ● | ●● | ● | ● | 80+ | 1400 | 41.9 | 49.1 |

Designer Series

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ● | ● | ● | 90+ | 350 | 5.4 | 7.5 |
| 1300lm | | ● | ● | ● | ● | 90+ | 700 | 11.4 | 14.3 |
| 2000lm | | ● | ● | ● | ● | 90+ | 700 | 17.1 | 20.1 |
| 3000lm | | ● | ● | ● | ● | 90+ | 1050 | 25.7 | 29.5 |
| 4500lm | | | ● | ● | ● | 90+ | 1400 | 41.8 | 49.2 |

Artist Series Vibrant Series V95

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 700lm | | ● | ●● | ● | ● | 80+ | 350 | 4.5 | 6.5 |
| 1300lm | | | ●● | ● | ● | 80+ | 700 | 9.6 | 12.3 |
| 2000lm | ● | ● | ●● | ● | ● | 80+ | 700 | 15.2 | 19.2 |
| 3000lm | | ● | ●● | ● | ● | 80+ | 1050 | 25.6 | 29.4 |
| 4000lm | | ● | ●● | ● | ● | 80+ | 1400 | 34.2 | 39.1 |

Beauty Series

| Nominal Flux | Colour Temperature (K) | | | | | CRI (Ra) | Drive Current (mA) | Module Wattage (W) | Total Circuit Wattage (W) |
|--------------|------------------------|------|------|------|------|----------|--------------------|--------------------|---------------------------|
| | 2200 | 2700 | 3000 | 3500 | 4000 | | | | |
| 1300lm | | ● | | | | 95 | 700 | 13.3 | 16.2 |
| 2000lm | | ● | | | | 95 | 1050 | 20 | 22.1 |